

Stealth Comfort - Approved Combination Chart - 2023							
Condenser Model	Compatible Air Handler BTUs	Air Handler BTU Range	Air Handlers				
			#1	#2	#3	#4	#5
SC-18Z-HH-M2	7K, 9K, 12K	11,880 - 24,120	7K	7K	X	X	X
			7K	9K	X	X	X
			9K	9K	X	X	X
			9K	12K	X	X	X
			12K	12K	X	X	X
SC-27Z-HH-M3	7k, 9K, 12K, 18K	15,840 - 32,160	7K	7K	7K	X	X
			9K	9K	9K	X	X
			9K	9K	12K	X	X
			9K	9K	X	X	X
			9K	12K	X	X	X
			9K	18K	X	X	X
			12K	12K	X	X	X
SC-36Z-HH-M4	7K, 9K, 12K, 18K, 24K	23,760 - 48,240	12K	18K	X	X	X
			7K	7K	7K	7K	X
			9K	9K	9K	9K	X
			9K	9K	9K	12K	X
			9K	9K	9K	18K	X
			9K	9K	12K	12K	X
			9K	9K	12K	18K	X
			9K	12K	12K	12K	X
			12K	12K	12K	12K	X
			9K	9K	9K	X	X
			9K	9K	12K	X	X
			9K	9K	18K	X	X
			9K	9K	24K	X	X
			9K	12K	12K	X	X
			9K	12K	18K	X	X
			9K	12K	24K	X	X
			9K	12K	24K	X	X
			12K	12K	18K	X	X
			12K	12K	24K	X	X
			12K	18K	18K	X	X
			9K	18K	X	X	X
			9K	24K	X	X	X
			12K	12K	X	X	X
			12K	18K	X	X	X
12K	24K	X	X	X			
18K	18K	X	X	X			
18K	24K	X	X	X			
24K	24K	X	X	X			
SC-42Z-HH-M5	7K, 9K, 12K, 18K, 24K	27,720 - 56,280	7K	7K	7K	7K	7K
			9K	9K	9K	9K	9K
			9K	9K	9K	9K	12K
			9K	9K	9K	9K	18K
			9K	9K	9K	12K	12K
			9K	9K	12K	12K	12K
			7K	7K	7K	7K	X
			9K	9K	9K	9K	X
			9K	9K	9K	12K	X
			9K	9K	9K	18K	X
			9K	9K	9K	24K	X
			9K	9K	12K	12K	X
			9K	9K	12K	18K	X
			9K	9K	12K	24K	X
			9K	9K	18K	18K	X
			9K	12K	12K	12K	X
			9K	12K	12K	18K	X
			12K	12K	12K	12K	X
			12K	12K	12K	18K	X
			9K	9K	12K	X	X
			9K	9K	18K	X	X
			9K	9K	24K	X	X
			9K	12K	12K	X	X
			9K	12K	18K	X	X
			9K	12K	24K	X	X
			9K	18K	18K	X	X
			9K	18K	24K	X	X
			12K	12K	12K	X	X
			12K	12K	18K	X	X
			12K	12K	24K	X	X
			12K	18K	18K	X	X
			12K	18K	24K	X	X
18K	18K	18K	X	X			
9K	24K	X	X	X			
12K	18K	X	X	X			
12K	24K	X	X	X			
18K	18K	X	X	X			
18K	24K	X	X	X			
24K	24K	X	X	X			

NOTES

Always put the largest BTU air handler on Zone #1. The organization of this chart is for the reader's convenience only. The air handlers do not have to be connected in the listed order.

IMPORTANT

Maximum Air Handlers = **134%** Rated Capacity
 Minimum Air Handlers = **66%** Rated Capacity
 If connected equipment does not meet these parameters efficiency and performance will drop significantly and will not be OEM approved



STEALTH